

WINCO®

Quality Generators Since 1927



HPS9000VE



Engine:

- Briggs & Stratton Vanguard V-Twin OHV
- EPA certified design for use with gasoline, LP and natural gas
- Commercial grade engine with cast iron cylinder sleeves
- 3 year warranty
- Special carburetor and secondary gas regulator allows the engine to operate on the most convenient fuel - gasoline, LP or natural gas
- Maintenance-free electronic ignition system
- Low oil protection helps prevent costly repairs and downtime

Generator End:

- 100% copper windings - longer life and improved motor starting
- Dampers, skewed rotors for <6% harmonic distortion
- Capacitor excitation, brushless operation

Features:

- 7 gallon steel fuel tank with fuel gauge
- Heavy duty 1"-14 gauge tubular steel cradle
- Industrial powder coat paint
- Electric/Recoil start (NG and LP operation requires electric start)
- Full receptacle package with circuit breaker protection
- 120/240 volt receptacle for connection to a temporary power distribution system or to a building electrical service with an approved manual transfer switch for emergency/standby use
- Vibration isolation for smooth operation
- Easy to move, convenient to store

Accessories (optional):

- Two-wheel dolly kit
- Generator cover
- Low pressure fuel solenoid kit
- 30 amp manual transfer switch kit
- Plug-in line voltage monitor
- 30 amp (NEMA L14-30P) plug

SURGE WATTS (1)	9000
CONTINUOUS WATTS (1)	8000
AMPS (1)	66.7/33.3
VOLTS	120/240
VOLTAGE REGULATION	+/- 5%
FREQUENCY REGULATION	+/- 3%
ENGINE BRAND	BRIGGS & STRATTON
ENGINE MODEL	VANGUARD
ENGINE STARTER (3)	ELECTRIC/RECOIL
ENGINE SPEED	3600 RPM
DISPLACEMENT	480 CC
ENGINE CYLINDERS	V-TWIN
LOW OIL PROTECTION	STANDARD
dBAAT 7 METERS	77
FUEL TANK	7 GAL
FUEL USE:	GASOLINE 1.3 gal/hr NATURAL GAS 180 ft³/hr - 183,600 BTU/hr LP GAS 1.9 gal/hr - 173,853 BTU/hr
FULL PRESSURE OIL LUBE WITH SPIN-ON FILTER	INCLUDED
MOTOR STARTING (CODE G) (1) (2)	4 HP
MAIN CIRCUIT BREAKER	35A
120 VOLT RECEPTACLES	4 x NEMA 5-20R 20A
120/240 VOLT RECEPTACLES	1 x NEMA L14-30R 30A
DIMENSIONS (LxWXH)	32.75" x 22.5" x 22"
NET WEIGHT	242
SHIP WEIGHT	267
WARRANTY (ENG/GEN) (4)	3 YRS / 2 YRS

NOTES: (1) Based on gasoline fuel. Derate 10% for LP gas and 20% for Natural Gas. (2) Code G capacitor start motor. (3) Electric start models include battery rack and cables, battery not included. BCI Group 20 or 24 HL, 12-volt, 300 CCA or larger battery required. (4) Prime Power Warranty 120 days. Contact your local Briggs & Stratton engine service center for engine warranty assistance.

Presented by:

TRI-FUEL ← LP GASOLINE NG
HOME POWER®

Toll Free: 1-800-733-2112
 sales@wincogen.com

www.wincogen.com

225 South Cordova Avenue
 Le Center MN, 56057